Product datasheet

OSRAM

POWERinvert 300W



Mains Power on the move Provides 230V power in your vehicle, perfect for life on the move



Silent operation Includes a low noise fan for minimal noise in use



Easy to use Simply connect to your invehicle 12V socket



Charges mobile devices Includes USB port for charging mobile devices



OSRAM POWERinvert 300W Compact Inverter 12V DC to 230V AC The OSRAM POWERinvert Modified Sine Wave Inverter 12V DC 300W is a compact solution for converting 12V DC power to 230V AC, delivering mains power directly from your car. Perfect for business trips, road trips, and holidays, this inverter supports devices up to 300W, such as laptops. It features a high-power 2.1A USB socket, ideal for charging smartphones and tablets. Easy to use, simply plug it into your vehicle's 12V DC socket. Its compact and lightweight design ensures convenient storage and portability.

Product datasheet

Technical data

Product information

USB sockets 2.1A	Yes
Electrical Data	
Input voltage range	10-15.5 V
Continuous Power Rating (up to 12 hours)	300 W
Output voltage	230v ac +/- 10%
Peak Power Rating (up to 200ms)	600 W

Physical Attributes & Dimensions





Length	180.0 mm
Width	121.0 mm
Height	54 mm

Dimensions & weight

Input Cable Gauge / Length	980.0 mm

Lifetime Data

Guarantee	2 years

Additional product data

Efficient at 75% load	89 %
Low Battery Alarm	Yes
Outpur Waveform	Modified sine wave

Programmable features

Thermal Protection	Yes

Product datasheet

Environmental & Regulatory Information

Information according Art. 33 of EU Regulation (EC) 1907/2006 (REACh)

Declaration no. in SCIP database

In work

Logistical Data

Product code	Product description	Packaging unit (Pieces/Unit)	Dimensions (length x width x height)	Volume	Gross weight
4062172406598	Modified Sine Wave Inverter 12V DC 300W	Folding carton box 1	202 mm x 90 mm x 130 mm	2.36 dm³	768.00 g
4062172406604	Modified Sine Wave Inverter 12V DC 300W	Shipping carton box 6	310 mm x 290 mm x 227 mm	20.41 dm³	4988.00 g

The mentioned product code describes the smallest quantity unit which can be ordered. One shipping unit can contain one or more single products. When placing an order, for the quantity please enter single or multiples of a shipping unit.

Download Data



File User instruction

POWERinvert 150 W 300 W 500 W

Application advice

For more detailed application information and graphics please see product datasheet.

Disclaimer

Subject to change without notice. Errors and omission excepted. Always make sure to use the most recent release.

